



OceanTRx7[™]

Maritime Stabilized VSAT System



Technical Note

Inertial Measurement Unit (IMU)

Document: TEC32-1664-001, Revision A January 2013

COMMUNICATION WITHOUT BOUNDARIES

Orbit Communication Systems Ltd. P.O.B. 42504, Israel, Tel: +(972) 9 892 2777, Fax: +(972) 9 885 5944 www.orbit-cs.com



Copyright

© 2013 Orbit Communication Systems Ltd. All rights reserved.

All product names are trademarks of Orbit Communication Systems Ltd.

Other names are the property of the respective owners.

No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic or otherwise, without the prior written permission of Orbit Communication Systems Ltd.

Disclaimer of Warranty

Orbit Communication Systems Ltd. has made every effort to ensure the accuracy and relevancy of the material in this document. It is expected that all sections of this document will be read thoroughly and that all information and procedures should be fully understood.

However, Orbit Communication Systems Ltd. assumes no responsibility for any errors that may appear in this document, and reserves the right to make changes to the document without notice.

Orbit Communication Systems Ltd. makes no warranty of any kind in regard to this document, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose.

Orbit Communication Systems Ltd. disclaims any responsibility for incidental or consequential damages in connection with the furnishing, performance or use of this document.

Parts of this document may be based on hardware or software developed by third-party vendors. Orbit Communication Systems Ltd. disclaims any responsibility for the accuracy of this document with respect to such hardware and software, and assumes no responsibility for incidental or consequential damages arising due to discrepancies between this document and such hardware or software.



Revision History and Control

Revision History

Rev #	Modified by	Date	Comments
Rev. A	Edox		



About this Manual

This manual is designed to guide you through the procedures required for maintaining the Inertial Measurement Unit (IMU) for the OceanTRx7[™] Maritime Satellite Communication System.

Text Conventions

Style	Indicates	Example
Text	Normal descriptive text	Contents
Text	Words or figures that appear on the screen or that should be typed The name of a file or directory	System Status
<text></text>	A key to be pressed	<esc></esc>
TEXT	The name of a hardware component	ANTENNA
Text	The name of a GUI element	Operation Screen
\triangleright	The description of a procedure	➢ To configure

Notations



Indicates important information that should be noted.



Indicates a potential hazard.



Indicates the safest method of installation or an operation that *must be adhered* to.



Effective Releases

This document is effective for Release 1 (R1) and Release 2 (R2) of the OceanTRx7[™] Maritime Satellite Communication System.

For a description of the changes between R1 and R2, refer to the *OceanTRx7™ Maritime Satellite Communication System Release Notes*.



Table of Contents

1	Intro	oduction	1
	1.1	Purpose	1
	1.2	Principles	1
	1.2.	1 Torque Table	1
	1.3	IMU Description	2
	1.4	Spare Kit Contents	3
	1.5	Required Tools and Parts	3
2	Pre	liminary Procedures	4
3	Rep	placing the IMU	5
	3.1	Removing the IMU	5
	3.2	Installing an IMU	7
4	Sof	ware	9
	4.1	Configuring the IMU Calibration File	9
	4.2	Updating the system with General Software update module (GSU) 1	0
	4.2.	1 Verify actual software version of the system units1	2
	4.3	Verifying System Function1	3
5	Арр	endix A: Replacing IMU's cable (R1 with R2)1	4
	5.1	Removing IMU's Cable (ANTENA R1)1	4
	5.2	Installing IMU's (R2) Cable1	5



1 Introduction

1.1 Purpose

The purpose of this Technical Note is to provide detailed instructions on how to replace and configure an IMU.

1.2 Principles

The following principles must be followed when performing the procedures in this Technical Note.

1.2.1 Torque Table

The following table provides the torque that should be used when tightening screws of the listed types, as relevant.

Screw Type	Torque
M8	25 ^N / _m
M6	10.2 ^N / _m
M5	6 ^N /m
M4	2.5 ^N /m
М3	1.35 ^N / _m

Tahle	1_1+	Torque	Values
1 abic		rorquo	valueo



1.3 IMU Description

A strap-down solid-state INERTIAL MEASUREMENT UNIT (IMU) is installed on the PEDESTAL and provides extremely accurate dynamic readings of the platform's sea movement to the ACU. The ACU stabilizes the ANTENNA accordingly in real-time via the SERVO SUBSYSTEM.

The IMU reports the following data:

- Pitch and roll Short-term data measured by two RATE-GYRO SENSORS dynamically integrated by the ACU with long-term data measured by two INCLINOMETERS.
- Yaw variations Short-term data measured by a RATE-GYRO SENSOR, dynamically integrated by the ACU with long-term yaw data received from the ship's gyrocompass.



Figure 1-1: Inertial Measurement Unit



1.4 Spare Kit Contents

The following table provides a list of the parts in the IMU spare kit.

Table 1-2: Spare Part Kit Contents

KIT32-1664-006-SP				
P/N	Description	Quantity		
30-0713-9-1	CABLE PEDESTAL TO IMU PANEL AL-7107	1		
30-0713-9-4	CABLE POWER BOX R2 TO IMU R1 AL-7107-SYS2	1		
H06016072001	SCKT CAP SCR M6X20 ST.ST.	4		
H20216091072	FLAT RD WASHER M6 SS 316	4		
H28216091072	HELIC SPR WASHER M6 SS 316	4		
L01323001	INERTIAL MEASUREMENT UNIT (IMU)	1		
PKG-049	PKG BOX 240X150X130mm RSC	1		

1.5 Required Tools and Parts

The following table provides a list of tools and customer-supplied parts that are needed to perform the procedures in this Technical Note.

Table 1-3: Required	Tools and Parts
---------------------	------------------------

Tool/Part Name	Notes	Figure
Allen key, 5mm		



2 Preliminary Procedures

The preliminary procedure described below must be performed before replacing the IMU.

- 1. Perform System Shut-Down of the vessel's main power AC Voltage terminal outside the RADOME.
- 2. Open the RADOME hatch.
- 3. Switch off the ADE POWER BOX at the ANTENNA PEDESTAL base (located inside the RADOME).
- 4. Manually rotate the PEDESTAL AXES to gain convenient access to the serviced unit.



In the following procedures, be very careful when tightening and loosening the screws with which the parts are assembled and attached to the system. Some of these screws are delicate and can be damaged by excess force. When using an Allen key make sure to insert the key all the way into the screw head to avoid thread stripping.



WARNING!

The Utility Outlet is connected directly to the vessel's AC voltage input terminals (125 VAC / 250 VAC). Therefore, there still exists live voltage at the Utility Outlet after disconnecting the power supply to the ADE using the Mains Power On/Off Switch.

Only qualified and authorized personnel are allowed to carry out system service/maintenance procedures.



3 Replacing the IMU

3.1 Removing the IMU

Step 1

Locate the IMU.-





Step 2

Disconnect the IMU'S connector.

Attention: When replacing an IMU (ANTENA R1) with an IMU (ANTENA R2) refer to Appendix A for a cable replacement description.

Step 3

Use a Philips screw driver to release and remove grounding cable.



Step 4

Remove four screws securing the IMU to the BASE PLATE, using a 5mm Allen key.



Step 5

Remove the IMU from the BASE PLATE.





3.2 Installing an IMU

Step 1

Make sure the IMU and the BASE PLATE surfaces are clean of any debris.



Step 2

Mount the IMU in its place on the BASE PLATE.

Note: The two LEAD PINS on the BASE PLATE.

Step 3

Secure the IMU to the BASE PLATE using a 5mm Allen key.





Connect the IMU cable to the IMU connector.





Step 5

Use a Philips screw driver to tighten the grounding cable to the IMU.





4 Software

After the IMU has been replaced, perform the software procedures in this chapter.

4.1 Configuring the IMU Calibration File

- 1. Start up the system (see the *OceanTRx7™ Installation and Operation Manual* for instructions).
- 2. Activate the MTSDOCK application on the CCU.
- 3. Open the ACU menu and select Connect. The Connect to ACU dialog box appears.

Connect to ACU			×
Network Address[: Po	rt] 192.9.200.10		
	OK (Enter)	Cancel (Esc)	
	EnterIE		

Figure 4-1: Connect to ACU Dialog Box

- Verify that the correct ACU IP address appears in the Network Address field and click OK (Enter). When the connection is established between the CCU and the ACU, a message box appears confirming the connection.
- 5. Open the ACU menu, select Calibration, then Put IMU Calibration.
- 6. Insert the USB flash drive supplied with the IMU IMUSAVE -> OK.



4.2 Updating the system with General Software update module (GSU)

- Request the latest GSU & MTSDOCK files (*GSUXXX.zip* and MtsDockCE.exe or MtsDock.exe) from Orbit.
- 2. Copy the zipped and the executable files to a USB flash drive.
- 3. Connect the flash drive to the USB port in the ${\tt CCU}$ front panel.
- 4. Run the MTSDOCK utility from the USB Flash drive or on external Laptop
- 5. Select ThisHost menu and chose General Software Update...
- 6. The Select ZIP Archive with Software Updates dialog box appears.

👍 Select ZIP Archive with Software Updates	X	
Look in: 📕 Version 1.3 for 7107 or Orsat MKIII 💌	← 🗈 📸 🐨	
Name	Date modified 🔶	
AL-7107-ACU(8044)_1.30.zip	21/11/2012 18:50	
AL-7107-CCU(8044)_1.30.zip	04/12/2012 21:17	
DualGSUpdate_1.30.zip 04/12/2012 16:56		
GSUpdate_1.30.zip 04/12/2012 16:56		
MtsDock-Host_PC_1.30.zip 21/11/2012 18:56		
<	•	
File name: GSUpdate_1.30.zip	Open	
Files of type: Zip Archive (*.zip)	Cancel	

Figure 4-2: Select ZIP Archive with Software Updates Dialog Box

6. Select the GSU file from the USB Flash drive.



If you are using a Laptop to perform the upgrade you have to NIC IP address within range with the system IP subnet (default 192.9.200.xx .255.255.255.0)



7. Click **Open (Enter)**. New dialog box will pop up ask to enter the ACU and the CCU IP address, Enter the address previous found.

Connect to ACU, CCU		×
ACU IP Adress[:Port]	[192.9.200.10]	•
CCU IP Adress[:Port]	192.9.200.22	•
0	< (Enter) Cancel (Esc)	
	Enter IP Address	

Figure 4-3: Connect ACU, CCU Message Box

- 4. Click Open (Enter). The automated upgrade process will start. It will update the ACU (VSATWORKS) executable, CCUs MTSVLINK and also the Servo Drives FIRMWARE if applicable.
- 11. Reboot prompt will be issued at end of the process. Reboot by pressing **OK**.





CCU IP Address will be asked only if the MTSDOCK is running from laptop connected to the system network. Otherwise the CCU IP will not appear

4.2.1 Verify actual software version of the system units

1. When communication is reestablished between the SBC/ACU and the CCU,

Click the Version command on the MTSLINK Menu Bar and verify that the new version was successfully installed and matches the software version used by the CCU.

Version	×
MTSVLink ACU	1.3 VS 4.12.2012 1.3 VS 20.11.2012
- Database	
	Cancel (Esc)

Figure 4-5: Version Message Box



Proceed to step 2 only for system equipped with Servo Drivers (OTRx X-XXX)

2. Open the **Config** on the **MtsLink** Menu Bar and select **Hardware ID** verify that the Servo drive version (000X-XXXXXXX) was successfully installed on all SD and matches the firmware version in the release note.



rdware ID			×			
Тире		– Serial Number –				
CPU	NANO-8044	ACH	0168			
NBB	L-Band	імп	2298			
BUC	40W TerraSat	NBB	4112016			
		BUC	TE5019776			
- Firmware Vers	sion					
NBR	0005	Azimuth Driver	0006-9DAC35A6			
BUC	FW IBUC v1.20	Elevation Driver	0006-9DAC35A6			
		PolSkew Driver	0006-9DAC35A6			
		Tilt Driver	0006-9DAC35A6			
Canad (Eas)						
Cancer (ESC)						

Figure 4-5: Hardware ID Message Box

4.3 Verifying System Function

1. Check the MTSVLINK System Messages window for any messages related to the IMU.

2. Go to: Config-> Hard ware ID ->	Type CPU	NANO-8044	Serial Number ACU	0094
Verify S.No. match.	NBR	L-Band 	IMU NBR BUC	2704 4411000 TE5019480
PIN: L01323001 S.No. 2704	NBR BUC	0005 FW IBUC v1.18	Azimuth Driver Elevation Driver PolSkew Driver Tilt Driver	0006-90AC35A6 0006-90AC35A6 0006-90AC35A6 0006-90AC35A6
MOD. VER. E12345678910				

3. Check the **Ship Coordinates** window and verify that the **Roll** and **Pitch** values are within normal range (±1°) and the **Yaw** value is consecutive to that of the compass readout.

X



5 Appendix A: Replacing IMU's cable (R1 with R2).

5.1 Removing IMU's Cable (ANTENA R1).

Step 1

Disconnect the IMU'S connector.

Step 2

Cut all tie wraps binding the IMU's cable.

Step 3

Release the IMU'S plug from the POWER CONNECTION BOX.

And remove the IMU'S plug.



Step 4

Remove IMU'S cable.



5.2 Installing IMU's (R2) Cable.

Step 1

Rout IMU'S new cable.



Step 2

Connect the IMU'S plug to the POWER CONNECTION BOX.

Hand tight the plugs screws.



Step 4 Connect the IMU'S cable to the IMU'S connector.



Step 5

Use tie wraps to secure IMU'S cable.

TEC32-1664-001